

## Hollywood Palladium Lighting Spec Sheet

Front Of House (FOH) 48/96 ETC Express Control Desk  
Snake Runs 2 x 3-pin XLR, 2 x 5-pin XLR 512 DMX (1 is spare), 2 x 120v Edison (1 is spare)

Dimming ETC Sensor 48ch x 2.4k Dimmer  
ETC Sensor 24ch x 2.4k Dimmer

Downstage Truss 5 x Thomas Pre Rigged Truss, Double Hung = 60 x Medium Par 64s

Upstage Truss 2 x Thomas Pre Rigged Truss, Double Hung = 24 x Narrow Par 64s

Inner Ring 3 x Par 64 6-Lamp Bars = 18 x Wide Par 64s  
6 x 1k 6" Fresnels

Outer Ring/Balcony 4 x Par 64 6-Lamp Bars = 24 x Wide Par 64s

House Power Location: Upstage left in the dimmer vault on the balcony level  
Lighting 200 AMPS 3-Phase terminates to Cam-Lok with reverse ground and neutral  
Sound 200 AMPS 3-Phase terminates to Cam-Lok with reverse ground and neutral

### House Right "B-Stage"

Downstage Truss 32' (four 8' sections) x Minibeam Truss  
4 X Par 64 6-Lamp Bars = 24 x Medium Par 64s

Upstage Truss 32' (four 8' sections) x Minibeam Truss  
4 X Par 64 6-Lamp Bars = 24 x Medium Par 64s

**\*PLEASE NOTE\*** Any use drawing more than 200 amps 3-Phase on either 200 amp service requires the use of a generator

The lighting system may be configured in many ways.

Depending on the configuration, additional power and dimmers may be required.